

## UT121<sup>22</sup> Series Smart Digital Multimeter



UT121A



UT121B



UT122



Large-screen



NCV detection



LIVE detection



Diode test  
(UT121B/UT122)



Auto-identification



LCD high  
voltage alert



Auto power off



Flashlight

UT121 series features large-screen & ultra-thin multimeters and auto-identification and it can display two measurement results at the same time, which is convenient for home and non-professional users. They are convenient and fast electronic tools.

Specifications	Range	UT121A	UT121B	UT122
AC voltage (V)	6V/60V/600V	±(1.0%+3)		±(1.0%+3)
	6V/60V/600V/750V		±(1.5%+3)	
AC voltage frequency (Hz)	10Hz~1kHz	±(0.5%+2)	±(0.5%+2)	±(0.5%+2)
DC voltage (V)	6V/60V/600V	±(0.7%+3)		±(0.5%+3)
	6V/60V/600V/1000V		±(1.2%+3)	
Resistance (Ω)	6000Ω/60KΩ/600KΩ/6MΩ/10MΩ	±(2.0%+5)		
	600Ω/6KΩ/60KΩ/600KΩ/6MΩ		±(2%+5)	
Capacitance (F)	60nF/600nF~600μF/6000uF~60mF		±(10%+5)	
	99.99nF/999.9nF~9.999μF/9.999mF~99.99mF			10%
Frequency (Hz)	10Hz~10MHz		±(0.1%+3)	±(0.1%+3)
Temperature (°C/°F)	-40°C~1000°C/-40°F~1832°F		±3°C/±6°F	±3°C/±6°F
Display count		6199	6199	6199
Dual display		√	√	√
Overvoltage category		CAT III 600V	CAT III 600V	CAT III 600V

